



SDR-120-12

■ Features :

- High efficiency 91% and low power dissipation
- 150% peak load capability
- Built-in active PFC function, PF>0.93
- Protections: Short circuit / Overload / Over voltage / Over temperature
- · Cooling by free air convection
- Can be installed on DIN rail TS-35/7.5 or 15
- UL 508 (industrial control equipment) approved
- EN61000-6-2(EN50082-2) industrial immunity level
- Built-in DC OK relay contact
- 100% full load burn-in test
- 3 years warranty

SDR-120-24





SDR-120-48



SPECIFICATION

MODEL

MODEL		SDR-120-12	SDR-120-24	SDR-120-48
	DC VOLTAGE	12V	24V	48V
ОИТРИТ	RATED CURRENT	10A	5A	2.5A
	CURRENT RANGE	0 ~ 10A	0 ~ 5A	0 ~ 2.5A
	RATED POWER	120W	120W	120W
	PEAK CURRENT	15A	7.5A	3.75A
	PEAK POWER Note.6	180W (3 sec.)		
	RIPPLE & NOISE (max.) Note.2	,	100mVp-p	120mVp-p
	VOLTAGE ADJ. RANGE	12 ~ 14V	24 ~ 28V	48 ~ 55V
	VOLTAGE TOLERANCE Note.3		±1.0%	±1.0%
	LINE REGULATION	±0.5%	±0.5%	±0.5%
	LOAD REGULATION	±1.0%	±1.0%	±1.0%
	SETUP, RISE TIME		s/115VAC at full load	± 1.0 /0
	HOLD UP TIME (Typ.)	20ms/230VAC 20ms/115VAC at full load		
	,,	88 ~ 264VAC 124 ~ 370VDC		
INPUT		47 ~ 63Hz		
	FREQUENCY RANGE	0.93/230VAC 0.96/115VAC at full load		
	POWER FACTOR (Typ.)	89%	91%	90.5%
	EFFICIENCY (Typ.)		9176	90.5%
	AC CURRENT (Typ.)			
	INRUSH CURRENT (Typ.)			
PROTECTION	LEAKAGE CURRENT	<1mA / 240VAC Normally under within 440 150% rated outsut accurate areas than 2 accords and then about down a/a value.		
	OVERLOAD	Normally works within 110 ~ 150% rated output power for more than 3 seconds and then shut down o/p voltage >150% rated power, constant current limiting with auto-recovery within 3 seconds and shut down o/p voltage after 3 seconds		
		1 /	, , , , , , , , , , , , , , , , , , ,	1 0
	OVER VOLTAGE	14 ~ 17V	29 ~ 33V	56 ~ 65V
	OVER TEMPERATURE	Protection type: Shut down o/p voltage, re-power on to recover		
		95°C ±5°C (TSW) detect on heatsink of power switch		
		Protection type: Shut down o/p voltage, recovers automatically after temperature goes down		
FUNCTION	DC OK REALY CONTACT RATINGS (max.)			
ENVIRONMENT	WORKING TEMP.	-25 ~ +70°C (Refer to "Derating Curve")		
	WORKING HUMIDITY	20 ~ 95% RH non-condensing		
	STORAGE TEMP., HUMIDITY	-40 ~ +85°C, 10 ~ 95% RH		
	TEMP. COEFFICIENT	±0.03%/°C (0~50°C)		
	VIBRATION	Component:10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes; Mounting: Compliance to IEC60068-2-6		
SAFETY & EMC (Note 4)	SAFETY STANDARDS	UI508, TUV EN60950-1 approved; (meet EN60204-1)		
	WITHSTAND VOLTAGE	I/P-O/P:3KVAC I/P-FG:2KVAC O/P-FG:0.5KVAC O/P-DC OK:0.5KVAC		
	ISOLATION RESISTANCE	I/P-O/P, I/P-FG, O/P-FG:>100M Ohms / 500VDC / 25°C / 70% RH		
	EMC EMISSION	Compliance to EN55011, EN55022 (CISPR22), EN61204-3 Class B, EN61000-3-2,-3		
	EMC IMMUNITY	Compliance to EN61000-4-2,3,4,5,6,8,11, EN55024, EN61000-6-2 (EN50082-2), EN61204-3, heavy industry level, criteria A, SEMI F47, GL approved		
OTHERS	MTBF	289.9K hrs min. MIL-HDBK-217F (25° C)		
	DIMENSION	40*125.2*113.5mm (W*H*D)		
	PACKING	0.67Kg; 20pcs/14.4Kg/1.16CUFT		
NOTE	Ripple & noise are measure Tolerance : includes set up The power supply is consid EMC directives. Installation clearances : 40r	ally mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature. The dat 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1 of 47 of parallel capacitor. To tolerance, line regulation and load regulation. The final equipment must be re-confirmed that it still meets of the component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets of the component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets of the component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets of the component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets of the component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets of the component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets of the component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets of the component which will be installed into a final equipment. The final equipment must be re-confirmed that it still meets of the component which will be installed into a final equipment.		

- 3 seconds max, please refer to peak loading curves.
 Derating may be needed under low input voltage. Please check the derating curve for more details.









